

Wattstopper Muti-Way Resi Vacancy Sensor 600W, White, Box Part No. CH-250-W



The CH-250 Passive Infrared (PIR) Multi-way Vacancy Sensor provides automatic lighting shutoff for a variety of applications including those with multiple switch locations. It is engineered to comply with specific provisions of California's Title 24-2013 energy code.

## Features & Benefits

Manual-on/automatic-off control with multi-way capability

Lighted pushbutton for visibility in darkened rooms

Ideal for hallways, stairwells and large rooms with multiple entrances Adjustable time delay

## Specifications

## General Info

| RoHS Conformant    | Yes  | DesignLights Consortium Qualified System | Yes              |
|--------------------|--|--|------------------|
| Additional Informa | tion   |  |                  |
| Product Height US  | 3.27 in  | Product Length US                        | 2.67 in          |
| Product Volume US  | 65.4 cu in                                     | Product Depth US                         | 5.0 in           |
| Product Width US   | 4.0 in   | Product Weight US                        | 0.45 lb          |
| Dimensions         |  |  |                  |
| Application Sector | Commercial                                     | Warranty Type                            | 5-Year           |
| Features           | IR (Infrared), Locator Light, Motion<br>Sensor | Switch Type                              | Motion<br>Sensor |
| UPC Number         | 754182923434                                   | Country Of Origin                        | China            |
| Product Line       | Wattstopper                                    | Color                                    | White            |
|                    |  |  |                  |

| Security            | Yes                              |               |           |
|---------------------|----------------------------------|---------------|-----------|
| Technical Informati | on                               |               |           |
| Response Frequency  | 60 Hz                            | Sensor Type   | Occupancy |
| Number of Buttons   | 1                                | Amperage      | 5 A       |
| Wattage             | 600 W                            | Mounting Type | Box       |
| Sensing Range       | 180 degrees,12 x 25 ft,600 sq ft | Voltage       | 120.0 V   |
| Connection Type     | Wired                            | Load          | 600W      |