

## Wattstopper PIR Ceiling Occupancy Sensor 120 linear sq. ft. 24 VDC, Part No. CX-100-3



Wattstopper's CX-100 Series Passive Infrared (PIR) Ceiling/Wall Sensors detect occupancy to control lighting in a wide variety of applications. These sensors provide superior coverage and performance with great energy savings.

## Features & Benefits

Turns lights on and off based on occupancy

User-adjustable time delay and sensitivity

ASIC technology reduces components and provides greater reliability Choice of four coverage patterns

Built-in light level sensor

Isolated relay for use with HVAC or other control systems

Automatic or manual-on operation when used with a BZ-150 Power Pack

## **Specifications**

## General Info

| Product Line       | Wattstopper | UPC Number        | 754182911288   |
|--------------------|-------------|-------------------|--|
| Country Of Origin  | China       | Features          | Indicator<br>Lights, IR<br>(Infrared),<br>Motion<br>Sensor |
| Application Sector | Commercial  | Warranty Type     | 5-Year   |
| Dimensions         |             |                   |  |
| Product Width US   | 3.0 in      | Product Weight US | 0.6 lb   |
| Product Volume US  | 67.5 cu in  | Product Depth US  | 4.5 in   |
| Product Height US  | 4.0 in      |                   |  |
|                    |             |                   |  |

| Additional Information |                     |  |        |  |  |
|------------------------|---------------------|--|--------|--|--|
| RoHS Conformant        | Yes                 | DesignLights Consortium Qualified System | Yes    |  |  |
| Security               | Yes                 |  |        |  |  |
| Technical Information  |                     |  |        |  |  |
| Sensor Type            | Occupancy           | Amperage                                 | 19 mA  |  |  |
| Sensing Range          | Up to 120 linear ft | Voltage                                  | 24.0 V |  |  |
| Connection Type        | Wired               |  |        |  |  |