



Wattstopper
PIR Ceiling Occupancy Sensor 120 linear sq. ft. 24 VDC,
Part No. CX-100-3



Wattstopper's CX-100 Series Passive Infrared (PIR) Ceiling/Wall Sensors detect occupancy to control lighting in a wide variety of applications. These sensors provide superior coverage and performance with great energy savings.

Features & Benefits

Turns lights on and off based on occupancy

User-adjustable time delay and sensitivity

ASIC technology reduces components and provides greater reliability

Choice of four coverage patterns

Built-in light level sensor

Isolated relay for use with HVAC or other control systems

Automatic or manual-on operation when used with a BZ-150 Power Pack

Specifications

General Info

| | | | |
|--------------------|-------------|---------------|--|
| Product Line | Wattstopper | UPC Number | 754182911288 |
| Country Of Origin | China | Features | Indicator Lights, IR (Infrared), Motion Sensor |
| Application Sector | Commercial | Warranty Type | 5-Year |

Dimensions

| | | | |
|-------------------|------------|-------------------|--------|
| Product Width US | 3.0 in | Product Weight US | 0.6 lb |
| Product Volume US | 67.5 cu in | Product Depth US | 4.5 in |
| Product Height US | 4.0 in | | |

Additional Information

| | | | |
|-----------------|-----|--|-----|
| RoHS Conformant | Yes | DesignLights Consortium Qualified System | Yes |
|-----------------|-----|--|-----|

| | |
|----------|-----|
| Security | Yes |
|----------|-----|

Technical Information

| | | | |
|-------------|-----------|----------|-------|
| Sensor Type | Occupancy | Amperage | 19 mA |
|-------------|-----------|----------|-------|

| | | | |
|---------------|---------------------|---------|--------|
| Sensing Range | Up to 120 linear ft | Voltage | 24.0 V |
|---------------|---------------------|---------|--------|

| | |
|-----------------|-------|
| Connection Type | Wired |
|-----------------|-------|