

# Pass and Seymour DR Series CFL/LED/Incandescent Single Pole/3-Way Rotary Dimmer, Preset, Black Part No. DRCL453PBK



Works with select dimmable CFL/LED or incandescent lighting loads and features a sleek, sculpted ergonomic design for smooth, easy operation and precise control.

#### Features & Benefits

Convenient Operation - Combines ON/OFF Decorator style switch with separate slider for dimming control

Constant memory returns lights to previous level after a power failure

Sleek, ergonomic design that matches well with other decorator products Higher ratings

Single pole and 3-way operation

Screw-pressure-plate back wire terminals to save time, space and money

Rating: 450W LED & CFL: 700W Incandescent: 120VAC 60Hz

## **Specifications**

### General Info

| Product Line      | Pass & Seymour            | Color              | Black         |
|-------------------|---------------------------|--------------------|---------------|
| Country Of Origin | China                     | Features           | Locator Light |
| Switch Type       | Push, Rotary              | Number of Switches | 1             |
| Warranty Type     | Limited Lifetime Warranty |                    |               |
| Dimensions        |                           |                    |               |
| Product Width US  | 1.74 in                   | Product Depth US   | 1.28 in       |
| Product Height US | 4.19 in                   |                    |               |

## Listing Agencies / 3rd Party Agencies

| cULus Listed       | Yes                |                    |                        |
|--------------------|--------------------|--------------------|------------------------|
| Technical Informat | ion                |                    |                        |
| Amperage           | 4.5 A              | Bulb Compatibility | CFL, Incandescent, LED |
| Number of Poles    | 3-Way, Single Pole | Wattage            | 700 W                  |
| Voltage            | 120.0 V            |                    |                        |