

## Wattstopper PIR Wall Switch Occupancy Sensor, 24V, Lt. Almond

Part No. PW-100-24-LA



The PW-100-24 passive infrared (PIR) low voltage wall switch sensor can turn lights OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

## Features & Benefits

High sensitivity and dense coverage for exceptional performance

Color-matched lens and low profile for appealing design

Defaults to Manual-ON operation for maximum energy savings

Low voltage input

Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience

## **Specifications**

## General Info

| Product Line       | Wattstopper                  | Color             | Light<br>Almond  |
|--------------------|------------------------------|-------------------|------------------|
| UPC Number         | 754182919192                 | Country Of Origin | China            |
| Features           | IR (Infrared), Motion Sensor | Switch Type       | Motion<br>Sensor |
| Application Sector | Commercial                   | Warranty Type     | 5-Year           |
| Dimensions         |                              |                   |                  |
| Product Width US   | 4.0 in                       | Product Weight US | 0.3 lb           |
| Product Volume US  | 63.0 cu in                   | Product Depth US  | 5.0 in           |
| Product Height US  | 3.15 in                      |                   |                  |

| Additional Information |   |  |            |  |
|------------------------|---|--|------------|--|
| RoHS Conformant        | Yes   | DesignLights Consortium Qualified System | Yes        |  |
| Security               | Yes   |  |            |  |
| Technical Informa      | ation   |  |            |  |
| Sensor Type            | Occupancy                                       | Number of Buttons                        | 1          |  |
| Amperage               | 20 mA   | Indicator                                | LED Light  |  |
| Sensing Range          | Major motion 35 x 30 ft,Minor motion 20 x 15 ft | Voltage                                  | 18 to 24 V |  |
| Connection Type        | Wired   |  |            |  |